

LITEGEAR INTERVENT RFC01 2,4G RF Controller/Dimmer 1 Channel

2.4GHz Wireless Transmission 4 Zone Control



Technical Details:

Power Consumption:	288 W
Operating Hours:	>30.000 h
Switching Cycles:	>100.000
Ambient Temperature (TA):	-20°C - 40°C
Housing Material:	plastic
Housing Color	white
Zones:	1
Channels:	1
Dimming:	1-100%
Transmission Frequency:	2,4 GHz
Dimensions	74,5x35,6x16,5 mm
Net Weight:	20 g
Warranty	3 years

Product information "LITEGEAR INTERVENT RFC01 2,4G RF Controller/Dimmer 1 Channel"

INTERVENT-SERIES: RF Receiver controller monochrome

- Radio Frequency receiver 2,4GHz maximum operation distance: 30m
- Wireless controller for 5-24V DC LED strip converter/dimmer monochrome and dual white1 channel
- Easy Set-Up and operation
- Can be connected to several remotes and set up in Zones/groups.
- individual smooth dimming
- an additional power supply 5-24V DC is needed max. 1200mA
- 2 outputs max. 6A
- Screw terminals

Applications:
Office, Shop and residential

- Controller 5-24V DC LED-Strip
- controlled via RF remote or Tuya, Smart Life App Gateway

compatible RF remotes or Gateways see accessories!

Information and Downloads:

