

LITEGEAR INTERVENT WRF42 2,4G RF Wall Controller



Product information "LITEGEAR INTERVENT WRF42 2,4G RF Wall Controller"

INTERVENT-SERIES: RF Wallcontroller dual white

- Radio Frequency remote 2,4GHz wallmount. maximum operation distance: 30m
- Wireless controller for 12-24V DC LED strip converter/dimmer monochrome and dual white max. 2 channels
- Easy Set-Up and operation
- 4 individually controllable zones and master function
- 9 build in dynamic modes with speed select
- 60 seconds delay off function
- Touch Display, with different sounds
- individual smooth brightness level and CCT light colour adjustment
- magnetic support
- power supply: 3V DC (2 x AAA battery, not included)
- transmitting power: 6 dBm
- Standby power consumption: 20µA

Applications:
Office, Shop and residential

- for unlimited compatible 12-24V DC LED-Strip controller receiver: converter/dimmer
- Dimming of 12V DC LED-bulbs for example. MR11/16

compatible RF converter:

Technical Details:

Ambient Temperature (TA):	-10°C - 40°C
Housing Material:	plastic
Housing Color	white
Zones:	4
Channels:	2
Dimming:	1-100%
Programs:	9
Transmission Frequency:	2,4 GHz
Dimensions	86x86x16,5 mm
Net Weight:	113 g
Warranty	3 years

Information and Downloads:

